




The ABM 4551 is the solution for receiving digital and analog TV. This long distance active outdoor antenna with 51 elements and reflector receives your TV signal even in the hardest conditions. Like all Funke antennas, the ABM 4551 can be used in a horizontal and vertical network.

Its quality, solid design and optimized reception over the complete band make the Funke ABM 4551 a modern and reliable TV partner for you!



General specifications

Funke art. nr. 228.127402

Preferred applications Outdoor digital or analogue reception Antenna principle

51 elements with active open dipole

and reflector

Amplifier principle Low noise single stage amplifier (AINF)

Windload (@ 120km/h) 98 N

Connection F-connector

Technical specifications

Output impedance 75 Ω

470 - 862 MHz Frequency range Channels UHF 21 - 69

14 – 16 dBi Antenna gain AINF gain 16 dB 30 - 32 dBi Total gain $42 - 24^{\circ}$ Horizontal beamwidth Vertical beamwidth $48 - 28^{\circ}$ Directivity (front / back) 26 dB 5 ± 0,5 V Input voltage Input current 30 mA typ.



Physical specifications

Length Antenna 1330 mm Weight Antenna 1,300 kg

Material Gold anodized aluminium

725 x 273 x 64 mm Dimensions Package (Ixwxh)

Weight Package 1,550 kg **Outer Carton** 10 Pallet 100

Contents

ABM 4551 Mast Clamp User Manual

Clearly the Best